



**Extension Unit**

Item	Address	bit	Descriptor	Set or Get	Value
1	0x900	0	AF	Set	
2	0x900	1	NA	NA	
3	0x900	2	Set Power Frequency	Set	
4	0x900	3	Power Frequency Value	Set	
5	0x900	4	Set Flip and Mirror	Set	
6	0x900	5	Mirror	Set	0/1: Off/On
7	0x900	6	Flip	Set	0/1: Off/On
8	0x900	7	NA	NA	
9	0x901	0	Set Lamp	Set	
10	0x901	1	Lamp Value	Set	0/1: Lamp Off/Lamp On
11	0x901	2	Set Photo/Text	Set	0/1: Enable / Disable
12	0x901	3	Photo/Text	Set	0/1: Photo / Text
13	0x901	4	NA	NA	
14	0x901	5	NA	NA	
15	0x901	6	NA	NA	
16	0x901	7	NA	NA	
17	0x902	0	Get Power Status	Get	0/1: Off/On
18	0x902	1	Get Freeze Status	Get	0/1: Off/On
19	0x902	2	Get Lamp Status	Get	0/1: Off/On
20	0x902	3	Get Flip Status	Get	0/1: Off/On
21	0x902	4	Get Mirror Status	Get	0/1: Off/On

Item	Address	Bit	Descriptor	Set or Get	Value
22	0x902	5	Get Power Frequency	Get	0/1 : 60Hz/50Hz
23	0x902	6	Get Photo/Text	Get	0/1 : Photo/Text
24	0x902	7	NA	NA	